

PUR35



FEATURES

- High performance cost effective machine
- Highest grade HEPA and carbon technology
- Simple to install and easy to relocate
- Filter blocked alarm to warn the operator
- Adjustable airflow

SPECIFICATIONS

| | |
|----------------|-------------|
| Voltage | 90v - 254v |
| Part Number | 0AL4170 |
| Wattage | 1.1kW |
| Frequency | 50Hz / 60Hz |
| Cabinet Height | 630mm |
| Cabinet Width | 370mm |
| Cabinet Depth | 520mm |
| Cabinet Weight | 37Kg |
| Sound Level | <60dBa |
| Airflow | 400m3/h |

INCLUDED AS STANDARD...

FILTERS



Main Filter Code
113860

Description
Chemical



Main Filter Code
113841

Description
HEPA



Pre-filter Code
200500

Description
F8 Pleat Pack

Find out more:

 www.purex.co.uk

 purex@purex.co.uk

 +44 (0)1405 746030

CONNECTION KIT

*Connection kit is included
see overleaf for options*

Machine Supplied With • 2 x Main Filters • 1 x Pre-filter • 1 x Connection Kit • 1 x Power Cable • 1 x Manual

OPTIONS


Connection Kits

Hose End Diameter


Hose Length

Purex Inlet Diameter


Code: 100107 **100mm** **3m** **100mm**




Code: 100105 **100mm** **2m** **100mm**




Code: 120270 **100mm** **1.5m** **100mm**




Code: 120292 **80mm** **1.3m** **100mm**



Code: 100194 **50mm** **2.5m** **100mm**




Code: 100193 **50mm** **3.5m** **100mm**



If you do not see a connection kit that fits your machine or pipework, please contact Purex or your representative

Interfacing



Interfacing can remotely start the Purex machine when the connected machine starts.

Interfacing can also warn the connected machine when the Purex machine is in alarm.

Take a look through our Interfacing Guide to see our extensive range of options



www.fumeextractionsystems.com
sales@purexusa.com
tel:(336) 288-1613